

GC3e Premium Security & Control Panel



eSeries. NEW FEATURES



eSeries Sensors

New eSeries encrypted sensors provide enhanced security while reducing the risk of takeovers.



Smart Areas™
Makes it easy to set up and use zone partitioning in homes and light commercial settings.



7\"/>



Video Playback and Slideshows
Demo and promo videos keep users in-the-know. Play user photo slideshows in standby mode.



Easy Upgrades
Support for traditional 2GIG and other legacy 345 sensors makes system upgrades easy.



Two-Way Voice
Best-in-class voice quality provides clear communication with monitoring services.



Front-Firing Speaker
Front-firing speaker delivers exceptional audio performance.



SPECIFICATIONS

- 7" Capacitive Touchscreen
- 8 Keypads
- 2 Wired Zones
- 100 Wireless Zones
- 100 Users
- Full Voice Response
- Built-In Dual Band WiFi 802.11

- Built-in Z-Wave
- Chime by Zone
- User-Replaceable Cell Radio
- Firmware Updates (Remote Over-the-Air and USB)
- Dimensions: 8.88" W x 5.70" H x 1.34" D

ELECTRICAL

VOLTAGE
Panel Input 12-14VDC
AC Adapter In 100-240VAC 50/60Hz 1.7 A
14VDC adapter included

RECHARGEABLE BACKUP BATTERY (included)
ALARM SOUNDER
85 decibels at 10 feet

Smart Areas™

Makes it easy to set up and use zone partitioning in homes and light commercial settings.



Main House



Home Office



Garage



Guest House

For installation and Setup guides, visit:
dealer.2gig.com/support/guides-and-manuals

For technical support in the USA and Canada: 855-2GIG-TECH (855-244-4832)
For technical support outside of the USA and Canada contact your regional distributor.



WARNING: This product can expose you to chemicals including ACRYLONITRILE, which is known to the State of California to cause cancer, and BISPHENOL A, which is known to the State of California to cause birth defects and reproductive harm. For more information go to www.P65Warnings.ca.gov.

The GC3e Panel is ETL Listed in North America and meets the safety standards for: U.S. 965 Household Fire Warning System Units, U.S. 1023 Household Burglar Alarm Units, U.S. 1635 Digital Alarm Communicator System Units, ANSI/ISA CP-01 Control Panel Standard Features for False Alarm Reduction, and the California State Fire Marshal (CSFM), Canada: ULC C1023 Canadian Standard for Household Burglar Alarm System Units and ULC C3545-02 Canadian Standard for Residential Fire Warning System Control Units. To meet the requirements of regulatory agencies, you must follow the installation guidelines. For details, visit: dealer.2gig.com.




NORTEK
SECURITY & CONTROL

Designed by Nortek Security & Control LLC in the U.S.A.
Made in China Patent # 9,298,148
©2019 Nortek Security & Control LLC. All Rights Reserved.

2GIG-LTEV1-A-GC3 GC3 Verizon CellSled Cell Radio Made for 2GIG GC3 Panels

SPECIFICATIONS

- 4G LTE with VoLTE for Two-Way Voice
- Easy-to-use CellSled technology allows end-users to replace the cell radio
- Works on Verizon Network
- US only
- Includes necessary antennas
- Requires FW v3.1.3 or newer



From NORTEK Security & Control

10011500A